
RYLR993 AT COMMAND SET

Contents

1	General information	2
2	Overview	2
3	AT commands	3
3.1	AT_RX_ERROR	4
3.2	AT command overview	4
3.3	Event table	6
3.4	General commands	6
3.4.1	AT	6
3.4.2	AT?	7
3.4.3	ATZ - MCU reset	7
3.4.4	AT+VL - Verbose level	8
3.4.5	AT+LTIME - Local time in UTC format	8
3.4.6	AT+OPMODE – Set operating mode	9
3.5	Keys, IDs and EUIs management	10
3.5.1	AT+APPEUI - Application identifier	10
3.5.2	AT+NWKKEY - Network root key	10
3.5.3	AT+APPKEY - Application root key	11
3.5.4	AT+APPSKEY - Application session key	12
3.5.5	AT+NWKSKEY - Network session key	13
3.5.6	AT+DADDR - Device address	13
3.5.7	AT+DEUI - Device EUI	14
3.5.8	AT+NWKID - Network ID	14
3.6	Join and send data on LoRa network	15
3.6.1	AT+JOIN - Join LoRa network	15
3.6.2	AT+LINKC - Link check request	15
3.6.3	AT+SEND - Send data to LoRa network	16
3.7	LoRa network management	16
3.7.1	AT+VER - Firmware version.....	16
3.7.2	AT+ADR - Adaptive data rate functionality	17
3.7.3	AT+DR - Data rate	17
3.7.4	AT+BAND - Active region	18
3.7.5	AT+CLASS - LoRa class.....	19
3.7.6	AT+DCS - Duty cycle settings.....	19
3.7.7	AT+JN1DL - Join delay on Rx window 1	20

3.7.8	AT+JN2DL - Join delay on Rx window 2	20
3.7.9	AT+RX1DL - Delay of the Rx window 1.....	21
3.7.10	AT+RX2DL - Delay of the Rx window 2.....	21
3.7.11	AT+RX2DR - Data rate of the Rx window 2.....	22
3.7.12	AT+RX2FQ - Frequency of the Rx window 2.....	22
3.7.13	AT+TXP - Transmit power	23
3.7.14	AT+PGSLOT - Ping slot.....	23
3.8	Radio test commands	24
3.8.1	AT+TTONE - RF tone test	24
3.8.2	AT+TRSSI - RF RSSI tone test.....	24
3.8.3	AT+TCONF - LoRa RF test configuration	24
3.8.4	AT+TTX - Packets to be sent for PER RF TX test	27
3.8.5	AT+TRX - Packets to be received for PER RF RX test.....	28
3.8.6	AT+TTH - RF Tx hopping test.....	29
3.8.7	AT+CERTIF - Module in LoRaWAN certification with join mode	30
3.8.8	AT+TOFF - RF test	30
3.9	Information.....	31
3.9.1	AT+BAT - Battery level.....	31
3.9.2	AT+TEMP – Temperature.....	31
4	Examples	32
4.1	Join and send in unconfirmed mode	32
4.2	Join and send in confirmed mode	32
4.3	Rx received data.....	32
4.4	Class B enable request.....	33

List of tables

Table 1.	Acronyms	2
Table 2.	AT commands	4
Table 3.	Event table	6

1. General information

The document applies to the REYAX RYLR993 module that are LoRa SOC core-based devices.
It compatible with LoRaWAN® 1.0.3 Specification.

Table 1. Acronyms

Acronym	Definition
ABP	Activation by personalization
ETSI	European telecommunications standards institute
LoRa	Long range radio technology
LoRaWAN	LoRa wide-area network
OTAA	Over-the-air activation
RF	Radio frequency
RSSI	Received signal strength indicator
SNR	Signal-to-noise ratio

2. Overview

The following sections contain the interface description, the AT commands definition, and the description of some use cases and of the embedded software.

3. AT commands

The AT command set is a standard developed by REYAX to control module. The command set consists of a series of short text strings for performing operations such as joining, dataexchange and parameters setting.

The AT commands are used to drive the LoRa module and to send data. The ATcommands are sent through the UART.

- Baud rate: 9600
- Data: 8 bits
- Parity: none
- Stop: 1 bit
- Flow control: none

All commands are of the form AT+XXX, with XXX denoting the command. The following command behaviors are available:

- AT+XXX? provides a short help of the given command (such as AT+DEUI?).
- AT+XXX is used to run a command (such as AT+JOIN).
- AT+XXX=? is used to get the value of a given command (such as AT+CFS=?).
- AT+XXX=<value> is used to provide a value to a command (such as AT+SEND=2:Hello).

Output of the commands is provided on the UART. The output format is typically:

```
<value><CR><LF>
<CR><LF><Status><CR><LF>
```

Considering:

- `<value><CR><LF>` is returned when `help AT+XXX?` and `get AT+XXX=?` commands are run.
- `<CR>` and `<LF>` stands for the carriage return and line feed.
- When no value is returned, then `<value><CR><LF>` is not returned at all.
- Every command, except `ATZ` (MCU reset), returns a status string, that is preceded and followed by `<CR><LF>`. Possible status are:
 - `OK`: command run correctly without error.
 - `AT_ERROR`: generic error
 - `AT_PARAM_ERROR`: parameter of the command is wrong.
 - `AT_BUSY_ERROR`: LoRa network is busy, so the command could not complete.
 - `AT_TEST_PARAM_OVERFLOW`: parameter is too long.
 - `AT_NO_NETWORK_JOINED`: LoRa network is not joined.
 - `AT_RX_ERROR`: error detection during the reception of the command

More details on each command description and examples are given in the next sections. Each command preceded by `#` is provided by the host to the module, then the return of the module is printed.

3.1 AT_RX_ERROR

In case of `AT_RX_ERROR`, the command is corrupted when received in `AT_Slave`. Hence the command is not run. However, in case of long commands, some spurious characters can still be in the queue, ready to be processed as a command. So, in case the user receives an `AT_RX_ERROR`, the user must first send `<CR><LF>` to purge the queue, and then send back the same command so that it is processed.

Example

```
# AT+APPKEY=2b:7e:15:16:28:ae:d2:a6:ab:f7:15:88:09:cf:4f:3c<CR><LF>
<CR><LF>AT_RX_ERROR<CR><LF> /* a RX error has been encountered */
<CR><LF>AT_ERROR<CR><LF> /* after the command, AT_Slave have processed "something" which is
not a command - that could result in an error */
# <CR><LF> /* newline to purge */
<CR><LF>AT_ERROR<CR><LF> /* purge could result in an error */
/* now it is ok to resend the command */
# AT+APPKEY=2b:7e:15:16:28:ae:d2:a6:ab:f7:15:88:09:cf:4f:3c<CR><LF>
```

3.2 AT command overview

Table 2. AT commands

Command	Parameters	Description
General Commands		
AT	None	Check if the interface is available.
AT	[?]	Help of all supported commands.
ATZ	None	Reset
AT+VL	[=verb_lvl], where verb_lvl = [0:3]	Sets/gets the verbose level.
AT+LTIME	[=?]	Gets the local time in UTC format.
Keys, IDs and EUIs management commands		
AT+APPEUI	[=01:02:03:04:05:06:07:08]	Sets/gets the application EUI.
AT+NWKEY	[=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C]	Sets/gets the network root key
AT+APPKEY	[=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C]	Sets/gets the application root key.

Command	Parameters	Description
AT+APPSKEY	[=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C]	Sets/gets the application session key.
AT+NWKSKEY	[=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C]	Sets/gets the network session key.
AT+DADDR	[=01:02:0A:0B]	Sets/gets the device address.
AT+DEUI	[=01:23:45:67:89:AB:CD:EF]	Sets/gets the module unique ID.
AT+NWKID	[=127]	Sets/gets the network ID.
LoRa join and send data commands		
AT+JOIN	[=mode] where mode = 0 (ABP) or mode = 1 (OTAA)	Joins the network.
AT+LINKC	-	Piggyback link check MAC command request to the next uplink
AT+SEND	[=port_nb:confirmedmode:data] where confirmedmode = 0 or 1.	Sends packets to the network.
LoRa network management commands		
AT+VER	[=?]	Gets the LoRaWAN version.
AT+ADR	[=adr_enable] where adr_enable = 0 or 1	Sets/gets the adaptive data rate functionality.
AT+DR	[=datarate] where datarate = [0:7]	Sets/gets the data rate.
AT+BAND	[=region] where region = [0:9]	Sets/gets the active region
AT+CLASS	[=class] where class = [A, B or C]	Sets/gets the LoRa class.
AT+DCS	[=duty cycle] where duty cycle = 0 or 1	Sets/gets duty cycle settings.
AT+JN1DL	[=delay] where delay in ms	Sets/gets the join delay on Rx window 1.
AT+JN2DL		Sets/gets the join delay on Rx window 2.
AT+RX1DL		Sets/gets the delay of the Rx window 1.
AT+RX2DL		Sets/gets the delay of the Rx window 2.
AT+RX2DR	[=datarate] where X = [0:7]	Sets/gets data rate of the Rx window 2.
AT+RX2FQ	[=freq] where freq in Hz	Sets/gets the frequency of the Rx window 2.
AT+TXP	[=txpow] where txpow = [0:7]	Sets/gets the transmit power.
AT+PGSLOT	[=periodicity]	Sets/gets the ping slot.
Radio tests commands		
AT+TTONE	None	Sets the RF tone test.
AT+TRSSI		Sets the RF RSSI tone test.
AT+TCONF	[=freq:pow:bw:sf:cr:lna:pa:mod:paylen:freqdev:lowdropt:BT] [=868000000:14:125:12:4/5:0:0:1:255:0:0:0 for example]	Sets/gets the config LoRa RF test.
AT+TTX	[=nb_packets_sent]	Sets the number of packets to be sent for PER RF Tx test.
AT+TRX	[=nb_packets_received]	Sets the number of packets to be received for PER RF Rx test.

Command	Parameters	Description
AT+CERTIF	[=mode] where mode = 0 (ABP) or mode = 1 (OTAA)	Sets the module in LoRaWAN certification with join mode.
AT+TTH	[=<Fstart>, <Fstop>, <FDelta>, <PacketNb>]	Starts RF Tx hopping test from Fstart to Fstop (in Hz or MHz), Fdelta in Hz
AT+TOFF	None	Stops RF tests.
Information command		
AT+BAT	None	Gets the battery level.

3.3 Event table

The table below details the events that the AT_Slave application sends as a notification to the host module.

Table 3. Event table

Event	Return value	Description
+EVT: JOINED	None	Notifies an host module has been join on the gateway by OTAA.
+EVT: JOIN FAILED	None	Notifies the host module has not completed the join transaction (ID/Keys error, Tx not received by the gateway, Rx not received or not decrypted). In this case, the AT+JOIN must be recalled.
+EVT:	:<port>:<size>:<payload>	Notifies the host module that an asynchronous frame has been received on a RX window with downlink frame.
+EVT:	RX_<slot>:<DR>:<RSSI>:<SNR>	Notifies the host module that an asynchronous frame has been received on a RX window with downlink parameters.
+EVT:	RX_<slot>:<DR>:<RSSI>:<SNR>:<DMODM>:<GWN>	Notifies the host module that an asynchronous frame has been received on a RX window with extended downlink parameters. This event replaces the previous event when at least one link check request (AT+LINKC) has been executed.
+EVT: SEND_CONFIRMED	None	Notifies the host module that a Tx frame has been acknowledge by the gateway.

3.4 General commands

3.4.1 AT

Description	Attention is used to check if the link is working properly.
Syntax	AT<CR>
Arguments	None
Response	None
Result code	<CR><LF>OK<CR><LF>

Example:

```
/* Example: check the AT link is working properly*/
# AT<CR>
<CR>
OK<CR>
```

3.4.2 AT?

Description	Provides the short help of all supported commands.
Syntax	AT?<CR>
Arguments	None
Response	None
Result code	<CR><LF>OK<CR><LF>

Example:

```
/* Example: Get the short help of ALL AT commands*/
# AT?<CR>
AT+<CMD>?
AT+<CMD>      : Run <CMD>
AT+<CMD>=<value> : Set the value
AT+<CMD>=?    : Get the value
<List of all commands help>
<CR>
OK<CR>
```

3.4.3 ATZ - MCU reset

Description	The command generates a NVIC reset: resets the whole system including radio and microprocessor.
Syntax	ATZ<CR>
Arguments	None
Response	None
Result code	None (NVIC_Reset action)

Example:

```
/* Example: set NVIC system reset */
# ATZ<CR>
APP_VERSION:      V1.1.0<CR>
MW_LORAWAN_VERSION: V2.3.0<CR>
MW_RADIO_VERSION: V1.1.0<CR>
##### DevEui: AA:BB:CC:DD:EE:FF:00:11<CR>
##### AppEui: 01:02:03:04:05:06:07:08<CR>
##### DevAddr: 12:34:56:78<CR>
Attention command interface<CR>
AT? to list all available functions<CR>
```

Note: *The displayed keys by command above after ##### (DevEUI, AppEui, and DevAddr) are just informative and not a command response.*

3.4.4 AT+VL - Verbose level

Description	Sets/gets the verbose level of the application.
Syntax	AT+VL=<verbose_level><CR> AT+VL=?<CR>
Arguments	<verbose_level>, the default is 1 (VLEVEL_L) 0: VLEVEL_OFF 1: VLEVEL_L 2: VLEVEL_M 3: VLEVEL_H
Response	<verbose_level><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: set verbose level */
# AT+VL=3<CR>
<CR>
OK<CR>

/* Example2: get verbose level */
# AT+VL=?<CR>
3<CR>
<CR>
OK<CR>
```

3.4.5 AT+LTIME - Local time in UTC format

Description	Gets the local time in UTC format.
Syntax	AT+LTIME=?<CR>
Arguments	None
Response	<local time><CR><LF>
Result code	<CR><LF>OK<CR><LF>

Example:

```
/* Example: Get the local time in UTC format */
#AT+ LTIME=?<CR>
LTIME:02h14m52s on 01/01/1970<CR>
<CR>
OK<CR> /* module returns the command error code */
```

3.4.6 AT+OPMODE – Set operating mode

Description	Select LoRaWAN mode or REYAX RYLR998 proprietary mode
Syntax	AT+OPMODE=<mode><CR> AT+OPMODE=?<CR>
Arguments	<mode>, the default is 0 (LoRaWAN mode) 0: LoRaWAN mode 1: REYAX RYLR998 proprietary mode *RYLR993 can't set up the NETWORKID, only accept the default NETWORKID=18 of the RYLR998. When entry this mode please refer to the AT command of RYLR998.
Response	<mode><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Example:

```
/* Example 1: set operating mode*/
#AT+OPMODE=1<CR>
<CR>
OK<CR>

/* Example 2: get operating mode*/
#AT+VL=?<CR>
1<CR>
<CR>
OK<CR>
```

3.5 Keys, IDs and EUIs management

3.5.1 AT+APPEUI - Application identifier

Description	Sets/gets the application EUI.
Syntax	AT+APPEUI=<id><CR> AT+APPEUI=?<CR>
Arguments	<id>, 8-byte value separated by ":" (hexadecimal format string)
Response	<id><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: set APP EUI */
# AT+APPEUI=01:02:03:04:05:06:07:08<CR>
<CR>
OK<CR>

/* Example2: get APP EUI */
# AT+APPEUI=?<CR>
01:02:03:04:05:06:07:08<CR>
<CR>
OK<CR>
```

3.5.2 AT+NWKEY - Network root key

Description	Sets/gets the network root key. This key is used only in OTAA mode.
Syntax	AT+NWKEY=<key><CR> AT+NWKEY=?<CR>
Arguments	<id>, 4-byte value separated by ":" (hexadecimal format string)
Response	<key><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: set NWK Key */
# AT+NWKEY=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example2: get NWK Key when #define KEY_EXTRACTABLE 1 */
# AT+NWKEY=?<CR>
2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example3: get NWK Key when #define KEY_EXTRACTABLE 0 */
# AT+NWKEY=?<CR>
<CR>
AT_ERROR<CR>
```

3.5.3 AT+APPKEY - Application root key

Description	Sets/gets the application root key. This key is used only in OTAA mode.
Syntax	AT+APPKEY=<key><CR> AT+APPKEY=?<CR>
Arguments	<key>, 16-byte value separated by ":" (hexadecimal format string)
Response	<key><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example1: set APP Key */
# AT+APPKEY=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example2: get APP Key when #define KEY_EXTRACTABLE 1 */
# AT+APPKEY=?<CR>
2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example3: get APP Key when #define KEY_EXTRACTABLE 0 */
# AT+APPKEY=?<CR>
<CR>
AT_ERROR<CR>

```

3.5.4 AT+APPSKEY - Application session key

Description	Sets/gets the application session key. This key is used only in OTAA and APB modes. In OTAA mode, this key is replaced during the derivation process with the application root key and JoinAccept response information.
Syntax	AT+APPSKEY=<key><CR> AT+APPSKEY=?<CR>
Arguments	<key>, 16-byte value separated by ":" (hexadecimal format string)
Response	<key><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Example:

```

/* Example1: set APP Session Key */
# AT+APPSKEY=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example2: get APP Session Key when #define KEY_EXTRACTABLE 1 */
# AT+APPSKEY=?<CR>
2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example3: get APP Session Key when #define KEY_EXTRACTABLE 0 */
# AT+APPSKEY=?<CR>
<CR>
AT_ERROR<CR>

```

3.5.5 AT+NWKSKEY - Network session key

Description	Sets/gets the network session key. This key is used in OTAA and ABP modes. In OTAA mode, this key is replaced during the derivation process with the network's root key and JoinAccept response information.
Syntax	AT+NWKSKEY=<key><CR> AT+NWKSEY=?<CR>
Arguments	<key>, 16-byte value separated by ":" (hexadecimal format string)
Response	<key><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Example:

```

/* Example1: set NWK Session Key */
# AT+NWKSKEY=2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example2: get NWK Session Key when #define KEY_EXTRACTABLE 1 */
# AT+NWKSKEY=?<CR>
2B:7E:15:16:28:AE:D2:A6:AB:F7:15:88:09:CF:4F:3C<CR>
<CR>
OK<CR>

/* Example3: get NWK Session Key when #define KEY_EXTRACTABLE 0 */
# AT+NWKSKEY=?<CR>
<CR>
AT_ERROR<CR>

```

3.5.6 AT+DADDR - Device address

Description	Sets/gets the device address.
Syntax	AT+DADDR=<address><CR> AT+DADDR=?<CR>
Arguments	<address>, 4-byte value separated by ":" (hexadecimal format string)
Response	<address><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example1: set device address*/
# AT+DADDR=01:02:0A:0B<CR>
<CR>
OK<CR>

/* Example2: get device address*/
# AT+DADDR=?<CR>
01:02:0A:0B<CR>
<CR>
OK<CR>

```


3.5.7 AT+DEUI - Device EUI

Description	Sets/gets the device EUI.
Syntax	AT+DEUI=<EUI><CR> AT+DEUI=?<CR>
Arguments	<EUI>, 8-byte value separated by ":" (hexadecimal format string)
Response	<EUI><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example1: set device EUI*/
# AT+DEUI=01:02:03:04:05:06:07:08<CR>
<CR>
OK<CR>

/* Example2: get device EUI */
# AT+DEUI=?<CR>
01:02:03:04:05:06:07:08<CR>
<CR>
OK<CR>

```

3.5.8 AT+NWKID - Network ID

Description	Sets/gets the network ID.
Syntax	AT+NWKID=<id><CR> AT+NWKID=?<CR>
Arguments	<id>, 1-byte decimal value from 0 to 127
Response	<id><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example1: set the network ID */
# AT+NWKID=127<CR>
<CR>
OK<CR>

/* Example2: get the network ID */
# AT+NWKID=?<CR>
127<CR>
<CR>
OK<CR>

```

3.6 Join and send data on LoRa network

3.6.1 AT+JOIN - Join LoRa network

Description	Join the LoRa network.
Syntax	AT+JOIN=<mode><CR>
Arguments	<mode> 0: join to a network by ABP 1: join to a network by OTAA
Response	+EVT:JOINED or +EVT:JOIN_FAILED
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example1: Join a network by ABP */
#AT+JOIN=0<CR>
+EVT:JOINED<CR> /* event: ABP configuration done. Ready to start Tx */
<CR>
OK<CR>

/* Example2: Join a network by OTAA (Success result) */
#AT+JOIN=1<CR>
<CR>
OK<CR>

+EVT:JOINED<CR> /* Event : OTAA join successful event */

/* Example3: Join a network by OTAA (Fail result) */
#AT+JOIN=1<CR>
<CR>
OK<CR>

+EVT:JOIN_FAILED<CR> /* Event : OTAA join failed event. LoRaWAN network offline or keys not
aligned with the network configuration */

```

3.6.2 AT+LINKC - Link check request

Description	Piggyback link check MAC command request to the next uplink. The DemodMargin and NbGateways output information is provided into the extended Rx events +EVT:RX.
Syntax	AT+LINKC<CR>
Arguments	None
Response	None
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example: Piggyback Link Check Request to the next uplink */
#AT+LINKC<CR>
<CR>
OK<CR>

```

3.6.3 AT+SEND - Send data to LoRa network

Description	Sends application packets with specified and AppPort and payload to LoRaWAN network.
Syntax	AT+SEND=<port>:<ack>:<payload><CR>
Arguments	<ul style="list-style-type: none"> <port>: application port to be transmitted <ack> <ul style="list-style-type: none"> 0: unconfirmed message 1: confirmed message <payload>: payload in hexadecimal format strings (maximum length is 242 bytes)
Response	+EVT:SEND_CONFIRMED
Result code	<pre><CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF> <CR><LF>AT_DUTYCYCLE_RESTRICTED<CR><LF> <CR><LF>AT_NO_NET_JOINED<CR><LF> <CR><LF>AT_BUSY_ERROR<CR><LF> <CR><LF>AT_CRYPTO_ERROR<CR><LF> <CR><LF>AT_ERROR<CR><LF></pre>

Examples:

```
/* Example1: Send a packet to the gateway in unconfirmed mode */
#AT+SEND=2:0:ABCD<CR> /* send a packet : "ABCD", with APP port is 2, unconfirmed message */
<CR>
OK<CR>

/* Example2: Send a packet to the gateway in confirmed mode */
# AT+SEND=10:1:7FFF<CR> /* send a packet : "7FFF", with APP port is 10, confirmed message */
<CR>
OK<CR>

+EVT:SEND_CONFIRMED
```

3.7 LoRa network management

3.7.1 AT+VER - Firmware version

Description	Gets the version of the AT_Slave firmware.
Syntax	<pre>APP_VERSION: Vx.y.z<CR><LF> MW_LORAWAN_VERSION: Va.b.c<CR><LF> MW_RADION_VERSION: Vd.e.f<CR><LF></pre>
Arguments	None
Response	<version><CR><LF>
Result code	<CR><LF>OK<CR><LF>

Example:

```
/* Example: Get the Application and Middleware versions */
#AT+VER=?
RYLR993_FW_VERSION: V0.1.0<CR>
MW_LORAWAN_VERSION: V2.3.0<CR>
MW_RADION_VERSION: V1.1.0<CR>
<CR>
OK<CR>
```

3.7.2 AT+ADR - Adaptive data rate functionality

Description	Sets/gets the adaptive data rate functionality.
Syntax	AT+ADR=<enabled><CR> AT+ADR=?<CR>
Arguments	<enabled> <ul style="list-style-type: none"> 0: ADR disabled 1: ADR enabled (default)
Response	<enabled><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example1: Disable ADR */
#AT+ADR=0<CR> /* Disable ADR */
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Check ADR status */
# AT+ADR=?<CR>
0<CR> /* module returns ADR status */
<CR>
OK<CR> /* module returns the command error code */

```

3.7.3 AT+DR - Data rate

Description	Sets/gets the Tx data rate.
Syntax	AT+DR=<data rate><CR> AT+DR=?<CR>
Arguments	<data rate> in the range [0,1,2,3,4,5,6,7]
Response	<data rate><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Note: To be able to set data rate, the ADR must be disabled.

Examples:

```

/* Example1: Set TX Data Rate */
#AT+DR=2<CR> /* Set TX Data Rate */
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get Data rate with Adaptive DataRate disabled */
#AT+ADR=?<CR>
0<CR>
<CR>
OK<CR>
# AT+DR=?<CR>
2<CR> /* module returns TX data rate */
<CR>
OK<CR>

/* Example3: Get Data rate with Adaptive DataRate enabled */
#AT+ADR=?<CR>
1<CR>
<CR>
OK<CR>
# AT+DR=?<CR>
<CR>
AT_ERROR<CR>

```

3.7.4 AT+BAND - Active region

Description	Sets/gets the active region.
Syntax	AT+BAND=<band><CR> AT+BAND=?<CR>
Arguments	<band>: number corresponding to active regions 0: AS923 1: AU915 5: EU868 6: KR920 7: IN865 8: US915<default> 9: RU864
Response	<band><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```

/* Example1: Set Active region */
#AT+BAND=0<CR> /* Set AS923 as active region*/
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get Active region */
# AT+BAND=?<CR>
5:EU868<CR> /* module returns Active region */
<CR>
OK<CR> /* module returns the command error code */

```

3.7.5 AT+CLASS - LoRa class

Description	Sets/gets the LoRa class.
Syntax	AT+CLASS=<class><CR> AT+CLASS=?<CR>
Arguments	<class>: must be A, B or C.
Response	<class><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_ERROR<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF> <CR><LF>AT_NO_CLASS_B_ENABLE<CR><LF> <CR><LF>AT_NO_NET_JOINED<CR><LF>

Examples:

```
/* Example1: Set the LoRa Class */
#AT+CLASS=C<CR> /* Set Class C on device */
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get the LoRa Class */
# AT+CLASS=?<CR>
C<CR> /* module returns Active Class */
<CR>
OK<CR> /* module returns the command error code */
```

3.7.6 AT+DCS - Duty cycle settings

Description	Sets/gets the duty cycle settings.
Syntax	AT+DCS=<dutyCycleEnable><CR> AT+DCS=?<CR>
Arguments	<dutyCycleEnable> 0: duty cycle disabled 1: duty cycle enabled
Response	<dutyCycleEnable><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Enable Duty cycle */
#AT+DCS=1<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get Duty cycle */
# AT+DCS=?<CR>
1<CR> /* module returns Duty cycle */
<CR>
OK<CR> /* module returns the command error code */
```

3.7.7 AT+JN1DL - Join delay on Rx window 1

Description	Sets/gets the join accept delay between the end of the Tx and the join Rx window 1 (in ms).
Syntax	AT+JN1DL=<delay><CR> AT+JN1DL=?<CR>
Arguments	<delay>: value in ms
Response	<delay><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set Join Delay on RX window 1*/
#AT+JN1DL=5000<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get Join Delay on RX window 1*/
# AT+JN1DL=?<CR>
5000<CR> /* module returns Join Delay on RX window 1 in ms*/
<CR>
OK<CR> /* module returns the command error code */
```

3.7.8 AT+JN2DL - Join delay on Rx window 2

Description	Sets/gets the join accept delay between the end of the Tx and the join Rx window 2 (in ms).
Syntax	AT+JN2DL=<delay><CR> AT+JN2DL=?<CR>
Arguments	<delay>: value in ms
Response	<delay><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set Join Delay on RX window 2*/
#AT+JN2DL=8000<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get Join Delay on RX window 2*/
# AT+JN2DL=?<CR>
8000<CR> /* module returns Join Delay on RX window 2 in ms*/
<CR>
OK<CR> /* module returns the command error code */
```

3.7.9 AT+RX1DL - Delay of the Rx window 1

Description	Sets/gets the delay between the end of the Tx and the Rx window 1 (in ms).
Syntax	AT+RX1DL=<delay><CR> AT+RX1DL=?<CR>
Arguments	<delay>: value in ms
Response	<delay><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set Delay on RX window 1*/
#AT+RX1DL=1500<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get Delay on RX window 1*/
# AT+RX1DL=?<CR>
1500<CR> /* module returns Delay on RX window 1 in ms*/
<CR>
OK<CR> /* module returns the command error code */
```

3.7.10 AT+RX2DL - Delay of the Rx window 2

Description	Sets/gets the delay between the end of the Tx and the Rx window 2 (in ms).
Syntax	AT+RX2DL=<delay><CR> AT+RX2DL=?<CR>
Arguments	<delay>: value in ms
Response	<delay><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set Delay on RX window 2*/
#AT+RX2DL=2500<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get delay on RX window 2*/
# AT+RX2DL=?<CR>
2500<CR> /* module returns Delay on RX window 2 in ms*/
<CR>
OK<CR> /* module returns the command error code */
```


3.7.11 AT+RX2DR - Data rate of the Rx window 2

Description	Sets/gets the Rx window 2 data rate (0-7 corresponding to DR_X).
Syntax	AT+RX2DR=<datarate><CR> AT+RX2DR=?<CR>
Arguments	<datarate>: value in range [0:15]
Response	<datarate><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set RX window 2 Data rate*/
#AT+RX2DR=5<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get RX window 2 Data rate */
# AT+RX2DR=?<CR>
5<CR> /* module returns RX window 2 Data rate */
<CR>
OK<CR> /* module returns the command error code */
```

3.7.12 AT+RX2FQ - Frequency of the Rx window 2

Description	Sets/gets the Rx window 2 frequency.
Syntax	AT+RX2FQ=<freq><CR> AT+RX2FQ=?<CR>
Arguments	<freq>: value in Hz
Response	<freq><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set RX window 2 Frequency */
#AT+RX2FQ=869535000<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get RX window 2 Frequency */
# AT+RX2FQ=?<CR>
869535000<CR> /* module returns RX window 2 Frequency */
<CR>
OK<CR> /* module returns the command error code */
```

3.7.13 AT+TXP - Transmit power

Description	Sets/gets the transmit power.
Syntax	AT+TXP=<TxPow><CR> AT+TXP=?<CR>
Arguments	<TxPow>: must be in the range of the region activated in the range [0:15].
Response	<TxPow><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set Transmit power */
#AT+TXP=3<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get Transmit power */
# AT+TXP=?<CR>
3<CR>          /* module returns Transmit power */
<CR>
OK<CR> /* module returns the command error code */
```

3.7.14 AT+PGSLOT - Ping slot

Description	Sets/gets the unicast ping slot periodicity.
Syntax	AT+PGSLOT=<periodicity><CR> AT+PGSLOT=?<CR>
Arguments	<periodicity>: periodicity to be transmitted, must be in the range [0:7] Ping slot periodicity is $2^{\text{periodicity}}$, in seconds.
Response	<periodicity><CR><LF>
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Example:

```
/* Example1: Set Ping Slot */
#AT+PGSLOT=4<CR> /* Set Ping Slot periodicity to 2^4= 16 seconds*/
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Set Ping Slot */
#AT+PGSLOT=?<CR>
4<CR>
<CR>
OK<CR> /* module returns the command error code */
```

3.8 Radio test commands

3.8.1 AT+TTONE - RF tone test

Description	Starts a RF tone test.
Syntax	AT+TTONE<CR>
Arguments	None
Response	None
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_BUSY_ERROR<CR><LF>

Example:

```
/* Example: starts a RF Tone test */
# AT+TTONE<CR>
[TimeDisplay]: Tx FSK Test<CR>
<CR>
OK<CR>
```

3.8.2 AT+TRSSI - RF RSSI tone test

Description	Starts a RF RSSI tone test.
Syntax	AT+TRSSI<CR>
Arguments	None
Response	<rssi_lvl><CR><LF>: value in dBm
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_BUSY_ERROR<CR><LF>

Example:

```
/* Example: starts a RSSI tone test */
# AT+TRSSI<CR>
[TimeDisplay]: Rx FSK Test<CR>
[TimeDisplay]:>>> RSSI Value= -7 dBm<CR>
<CR>
OK<CR>
```

3.8.3 AT+TCONF - LoRa RF test configuration

Description	Sets/gets the LoRa RF test configuration.
Syntax	AT+TCONF=<freq>:<pow>:<bw>:<sf>:<cr>:<lna>:<pa>:<mod>:<paylen>:<freq dev>:<lowdropt>:<BT><CR> AT+TCONF=?<CR>

Arguments	<ul style="list-style-type: none"> • <freq>: frequency in Hz • <pow>: Tx power in range [-9:22] dBm • <bw>: <ul style="list-style-type: none"> – LoRa (in kHz) <ul style="list-style-type: none"> ‡ 0: 7.8125 ‡ 1: 15.625 ‡ 2: 31.25 ‡ 3: 62.5 ‡ 4: 125 ‡ 5: 250 ‡ 6: 500 – FSK: 4800 to 467000 Hz • <sf>: <ul style="list-style-type: none"> – LoRa: SF5 to SF12 bit/s – FSK: 600 to 300000 bit/s • <cr>: LoRa only <ul style="list-style-type: none"> – 1: 4/5 – 2: 4/6 – 3: 4/7 – 4: 4/8 • <lna>: low-noise amplifier <ul style="list-style-type: none"> – 0: Off – 1: On • <pa>: PA boost <ul style="list-style-type: none"> – 0: Off – 1: On • <mod>: modulation <ul style="list-style-type: none"> – [0]: FSK – 1: LoRa – 2: BPSK(Tx) • <paylen>: payload length 1 to 256 • <freqdev>: FSK only 4800 to 467000 • <lowdropt>: low DR optimization, LoRa only <ul style="list-style-type: none"> – 0: Off – 1: On – 2: Auto (1 when SF11 or SF12, 0 otherwise) • <BT>: FSK only <ul style="list-style-type: none"> – 0: no Gaussian filter applied – 1: BT = 0,3 – 2: BT = 0,5 – 3: BT = 0,7 – 4: BT = 1
-----------	---

Response	<ul style="list-style-type: none"> • Freq= <freq> Hz<CR> • Power= <pow> dBm<CR> • Bandwidth= <bw> (=125000 Hz)<CR> • SF= <sf><CR> • CR= <cr> (=4/5)<CR> • LNA State= <lna><CR> • PA Boost State= <pa><CR> • Modulation <mod><CR> • Payload len= <paylen> Bytes<CR> • <freqdev><CR> • LowDRopt[0 to 2]= <lowdropt><CR> • <BT><CR>
Result code	<pre><CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF></pre>

Note: <pa>, <freqdev>, <lowdropt> and <BT> arguments are required by the command syntax but are not used on the B-L072Z-LRWAN1 platform.

Examples:

```
/* Example1: Set LoRa RF test configuration */
#AT+TCONF=868000000:14:4:12:4/5:0:0:1:16:25000:2:3<CR>
<CR>
OK<CR> /* module returns the command error code */

/* Example2: Get LoRa RF test configuration */
# AT+TCONF=?<CR>
1: Freq= 868000000 Hz<CR>
2: Power= 14 dBm<CR>
3: Bandwidth= 4 (=125000 Hz)<CR>
4: SF= 12<CR>
5: CR= 1 (=4/5)<CR>
6: LNA State= 0<CR>
7: modulation LORA<CR>
8: Payload len= 16 Bytes<CR>
can be copy/paste in set cmd: AT+TCONF=868000000:14:4:12:4/5:0:0:1:16:25000:2:3<CR>
<CR>
OK<CR>
```

3.8.4 AT+TTX - Packets to be sent for PER RF TX test

Description	Starts a PER RF TX test with the number of packets to be sent.
Syntax	AT+TTX=<nb_packets><CR>
Arguments	<nb_packets>
Response	None
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF> <CR><LF>AT_BUSY_ERROR<CR><LF>

Example:

```
/* Example: Starts a PER RF TX test with the number of packets to be sent. */
# AT+TTX=4<CR>
[TimeDisplay]:Tx Test<CR>
[TimeDisplay]:Tx Test: Packet 1 of 4<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Test: Packet 2 of 4<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Test: Packet 3 of 4<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Test: Packet 4 of 4<CR>
[TimeDisplay]:OnTxDone<CR>
<CR>
OK<CR>
```

3.8.5 AT+TRX - Packets to be received for PER RF RX test

Description	Starts a PER RF RX test with the number of packets to be received.
Syntax	AT+TRX=<nb_packets><CR>
Arguments	<nb_packets>
Response	None
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF> <CR><LF>AT_BUSY_ERROR<CR><LF>

Example:

```

/* Example: Starts a PER RF RX test with the number of packets to be received. */
# AT+TRLRA=4<CR>
[TimeDisplay]:PRE OK<CR>
[TimeDisplay]:HDR OK<CR>
[TimeDisplay]:OnRxDone<CR>
[TimeDisplay]:RssiValue=-7 dBm, SnrValue=7<CR>
[TimeDisplay]:Rx: 1 of 4 >>> PER= 0 %<CR> /* PER percentage is updated/displayed after each
reception*/
[TimeDisplay]:PRE OK<CR>
[TimeDisplay]:HDR OK<CR>
[TimeDisplay]:OnRxDone<CR>
[TimeDisplay]:RssiValue=-7 dBm, SnrValue=6<CR>
[TimeDisplay]:Rx: 2 of 4 >>> PER= 0 %<CR> /* PER percentage is updated/displayed after each
reception*/
[TimeDisplay]:PRE OK<CR>
[TimeDisplay]:HDR OK<CR>
[TimeDisplay]:OnRxDone<CR>
[TimeDisplay]:RssiValue=-7 dBm, SnrValue=5<CR>
[TimeDisplay]:Rx: 3 of 4 >>> PER= 0 %<CR> /* PER percentage is updated/displayed after each
reception*/
[TimeDisplay]:PRE OK<CR>
[TimeDisplay]:HDR OK<CR>
[TimeDisplay]:OnRxDone<CR>
[TimeDisplay]:RssiValue=-7 dBm, SnrValue=6<CR>
[TimeDisplay]:Rx: 4 of 4 >>> PER= 0 %<CR> /* PER percentage is updated/displayed after each
reception*/
<CR>
OK<CR>

```

3.8.6 AT+TTH - RF Tx hopping test

Description	Starts RF Tx hopping test from Fstart to Fstop, with Fdelta steps.
Syntax	AT+TTH=<Fstart>,<Fstop>,<FDelta>,<nb_packets><CR>
Arguments	<ul style="list-style-type: none"> <Fstart>: frequency start (in Hz or MHz) <Fstop>: frequency stop (in Hz or MHz) <FDelta>: frequency bandwidth (in Hz) <nb_packets>: number of packets to be sent
Response	None
Result code	<CR><LF> OK <CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF> <CR><LF>AT_BUSY_ERROR<CR><LF>

Example:

```

/* Example: set TX hopping test from 868 to 868,5 MHz with 6 steps of 100 kHz */

# AT+TTH=868000000,868500000,100000,6<CR>
[TimeDisplay]: Tx Hop at 868000000Hz. 0 of 6<CR>
[TimeDisplay]:Tx LoRa Test<CR>
[TimeDisplay]:Tx 1 of 1<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Hop at 868100000Hz. 1 of 6<CR>
[TimeDisplay]:Tx LoRa Test<CR>
[TimeDisplay]:Tx 1 of 1<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Hop at 868200000Hz. 2 of 6<CR>
[TimeDisplay]:Tx LoRa Test<CR>
[TimeDisplay]:Tx 1 of 1<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Hop at 868300000Hz. 3 of 6<CR>
[TimeDisplay]:Tx LoRa Test<CR>
[TimeDisplay]:Tx 1 of 1<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Hop at 868400000Hz. 4 of 6<CR>
[TimeDisplay]:Tx LoRa Test<CR>
[TimeDisplay]:Tx 1 of 1<CR>
[TimeDisplay]:OnTxDone<CR>
[TimeDisplay]:Tx Hop at 868500000Hz. 5 of 6<CR>
[TimeDisplay]:Tx LoRa Test<CR>
[TimeDisplay]:Tx 1 of 1<CR>
[TimeDisplay]:OnTxDone<CR>
<CR>
OK<CR>

```


3.8.7 AT+CERTIF - Module in LoRaWAN certification with join mode

Description	Starts the module in LoRaWAN certification and with the choice of join mode.
Syntax	AT+CERTIF=<mode><CR>
Arguments	<mode> 0: join to a network by ABP 1: join to a network by OTAA
Response	+EVT:JOINED +EVT:JOIN_FAILED
Result code	<CR><LF>OK<CR><LF> <CR><LF>AT_PARAM_ERROR<CR><LF>

Examples:

```
/* Example1: Set the module in LoRaWAN certification and Join network by ABP */
#AT+CERTIF=0<CR>
+EVT:JOINED<CR> /* event: ABP configuration done. Ready to start Tx */
<CR>
OK<CR>

/* Example2: Set the module in LoRaWAN certification and Join network by OTAA */
#AT+CERTIF=1<CR>
<CR>
OK<CR>

+EVT:JOINED<CR> /* Event : OTAA join successful event */
```

3.8.8 AT+TOFF - RF test

Description	Stops the RF test.
Syntax	AT+TOFF<CR>
Arguments	None
Response	None
Result code	<CR><LF>OK<CR><LF>

Example:

```
/* Example: stops RF test */
# AT+TOFF<CR>
Test Stop<CR>
<CR>
OK<CR> /* module returns the command error code */
```

3.9 Information

3.9.1 AT+BAT - Battery level

Description	Gets the battery level (in mV).
Syntax	AT+BAT=?<CR>
Arguments	None
Response	<level><CR><LF>: value is in mV
Result code	<CR><LF>OK<CR><LF>

Example:

```
/* Example: Get the battery level in mV */
#AT+ BAT=?<CR>
3300<CR> /* battery level in mV */
<CR>
OK<CR> /* module returns the command error code */
```

3.9.2 AT+TEMP – Temperature

Description	Gets the temperature of module (in Celsius degree °C).
Syntax	AT+TEMP=?<CR>
Arguments	None
Response	<Celsius degree><CR><LF>: value is in Celsius degree.
Result code	<CR><LF>OK<CR><LF>

Example:

```
/* Example: Get the temperature */
#AT+TEMP=?<CR>
25<CR> /* value is in Celsius degree. */
<CR>
OK<CR> /* module returns the command error code */
```

4. Examples

Here are some basic examples that describe how to use the AT commands. In the following sections, commands provided by the host are preceded by #, and comments are embraced with /* */.

4.1 Join and send in unconfirmed mode

```
/* Check AT Link is OK */
#AT<CR>
<CR>
OK<CR>
/* Join in OTAA mode */
#AT+JOIN=1<CR>
+EVT:JOINED<CR> /* Event: OTAA join successful event */
<CR>
OK<CR>
/* Network is joined, now data can be sent */
#AT+SEND=50:0:01234ABCD<CR> /* Send hexadecimal values in unconfirmed mode to port 50 */
<CR>
OK<CR>
```

4.2 Join and send in confirmed mode

```
/* Check AT Link is OK */
#AT<CR>
<CR>
OK<CR>
/* Join in OTAA mode */
#AT+JOIN=1<CR>
+EVT:JOINED<CR> /* Event: OTAA join successful event */
<CR>
OK<CR>
/* Network is joined, now data can be sent */
#AT+SEND=50:1:01234ABCD<CR> /* Send hexadecimal values in confirmed mode to port 50 */
+EVT:SEND_CONFIRMED<CR>
<CR>
OK<CR>
```

4.3 Rx received data

It is possible to retrieve data sent from a specified port, when +EVT:RX is received.

```
/* Check AT Link is OK */
#AT<CR>
<CR>
OK<CR>
/* Join in OTAA mode */
#AT+JOIN=1<CR>
JOINED<CR> /* Event: OTAA join successful event */
<CR>
OK<CR>
/* Network is joined, now data can be sent */
#AT+SEND=50:0:01234ABCD<CR> /* Send hexadecimal values in unconfirmed mode to port 50 */
<CR>
OK<CR>
+EVT:50:4:ABCD<CR> /*Receive downlink frame */
+EVT:RX_1, DR 0, RSSI -49, SNR 5 <CR> /*Receive downlink parameters */
```

4.4 Class B enable request

The example below shows how to do a Class B request through an AT command sequence.

```

/* Join request in OTAA mode */
#AT+JOIN=1<CR>
<CR>
OK<CR>
/* wait for few seconds to wait for join to complete */
+EVT:JOINED<CR> /* end-device has joined the network */

/* now the network is joined, a request to enter into a Class B mode can be made */
#AT+CLASS=B<CR> /* Request to switch to Class B "enable" */
OK<CR>

/* A built-in MAC message is sent to the network to acquire the system time "Device Time
Req" */
#AT+SEND=50:0:0123<CR> /* Send data will allow piggybacking the MAC Device Time Req - could
be a dummy message */
OK<CR>

/* --> MAC Ping Device Time ANS is received by end-node in hidden way */
#AT+CLASS=?<CR>
B, S0<CR> /* Beacon Acquisition on-going */
OK<CR>
/* Loop on AT+CLASS=? until Beacon Acquisition on-going */

#AT+CLASS=?<CR>
B, S1<CR> /* Beacon Acquisition locked */
OK<CR>

#AT+PGSLOT=4<CR> /* Set Ping Slot periodicity to 2^4= 16 seconds and Send PingSlotInfoReq */
OK<CR>
/* --> MAC Ping Slot Info ANS is received by end-node in hidden way */

/* now the end-node is Class B "enable" */
#AT+CLASS=?<CR>
B<CR> /*Class B "enable"*/
OK<CR>

/* example: Local Time can be requested */
#AT+LTIME=?<CR>
LTIME:01h01m01s on 01/01/2021<CR>
<CR>
OK<CR>

```